

# Beacon Receiver

## TECHNICAL SPECIFICATIONS

The iNetVu® BR300L 19" rack mount Beacon Receiver is a high performance unit designed to track the power density of a satellite beacon in real time. It supplies a DC voltage output that is linearly proportional to the beacon power by utilizing a true, RMS - responding power detector.

The BR300L has been specifically designed to work seamlessly with all iNetVu® controllers and antenna platforms.



**Buy Now!**



### System

Input Frequency	930 MHz - 2300 MHz
Pre-detection Bandwidth	50 kHz
Input Level	- 90 dBm (Min.), -30 dBm (Max.)
Frequency Tuning	10 kHz steps
Frequency Adjust	Front panel or remotely
AFC	± 23 kHz
Threshold	45 dB-Hz, for acquisition
Input Impedance	75 Ohm
Input Connector	Type F, Female
Output Impedance	100 Ohm, Single ended
Output Connector	Terminal Plug & BNC Female
Tracking Gradient	0.5 V/dB
Tracking Response	0 to +10 VDC
System Level Range	60 dB
System Level Adjust	0 to 60 dB, 0.5 dB Steps
Frequency Stability	<1 ppm, 0° to +50° C (32° to 122° F)
Frequency Reference	10 MHz (Internal)
Phase Noise	>75 dB-Hz, 1 kHz from Carrier
Alarms	Unit Lock
Alarm Relay	Form-C
External LNB Power	+18VDC, Switched, In/Out, 500ma, (Max.)
Front Panel Display	Vacuum Fluorescent
M & C	RS-232 or RS-422/485 switched on rear panel
M & C Connector	DB-9, Female

### Environmental

Operating Temperature	0° to +50° C (32° to 122° F)
Storage Temperature	-40° to +70° C (-40° to +158° F)
Humidity	95% RH @ 40° C

### Physical

Operating Temperature	0° to +50° C (32° to 122° F)
Storage Temperature	-40° to +70° C (-40° to +158° F)
Humidity	95% RH @ 40° C

### Shipping dimensions

Receiver box:  
56 cm x 51 cm x 13 cm (22" x 20" x 5"), 3.7 kg (8 lbs)

**Note:** For input impedance and input connector, 50 Ohm N or SMA Type is available.



**Digisat International Inc.**  
4195 W. New Haven Ave., Suite 15  
Melbourne, FL 32904  
USA  
+1-321-676-5250  
Email: sales@digisat.org  
http://www.digisat.org

