

**DCP 2150**  
**DCP21501FK000**  
**DC Block/Power Inserter**

**General Description:**

The **DCP21501FK000** is designed to permit independent Power Supply Operation for LNAs, Up/Downconverters, and Line Amplifiers by providing a method for breaking the DC continuity and re-inserting DC power. The DC Power Supply is included for the utmost in installation convenience.

**Specifications:**

<b>Frequency:</b>	270-2150 MHz
<b>Insertion Loss:</b>	1.0 dB $\pm$ 1.0 dB
<b>Frequency Response:</b>	1.0 dB
<b>Return Loss:</b>	14 dB
<b>Input Voltage</b>	100-240 VAC @ 50-60 Hz
<b>Voltage Output:</b>	18 V $\overline{\text{---}}$ @ 1 Amp
<b>RF Connectors:</b>	Type F, 75 $\Omega$
<b>DC Connectors:</b>	Terminal block
<b>Mechanical:</b>	3.25" H x 3.25" W x 1.25" D
<b>Weight:</b>	2.0lb gross (boxed) 1.6lbs net
<b>Certifications:</b>	CE



**Buy Now!**

